

| Key Specifications | UTD1025CL | UTD1050CL | UTD1025DL | UTD1050DL |
|------------------------------|--|-----------------|------------------|-----------------|
| Bandwidth | 25MHz | 50MHz | 25MHz | 50MHz |
| Channels | 1 | | 2 | |
| Sampling rate | 200MSa/s | | 250MSa/s | |
| Rise time | ≤14ns | ≤7ns | ≤14ns | ≤7ns |
| Memory depth | 12kpts | | | |
| Vertical scale (V/div) | 5mV/div~20V/div | | | |
| Time base scale (s/div) | 10ns/div~50s/div | 5ns/div~50s/div | 10ns/div~50s/div | 5ns/div~50s/div |
| Storage methods | Setup, waveform, bitmap | | | |
| Trigger types | Edge, pulse width, video, slope | | | |
| Standard interface | Mini USB | | | |
| Multimeter Specifications | Range | | | Accuracy |
| DC voltage (V) | 400mV/ 4V/ 40V/ 400V | | | ±(1%+5) |
| AC voltage (V) | 400mV/ 4V/ 40V/ 400V | | | ±(1.2%+5) |
| DC current (A) | 400μA/ 4000μA | | | ±(1.2%+5) |
| | 40mA/ 4000mA | | | ±(1%+5) |
| | 4A | | | ±(1.5%+5) |
| AC current (A) | 400μA/ 4000μA | | | ±(2%+5) |
| | 40mA/ 4000mA | | | ±(1.5%+5) |
| | 4A | | | ±(2.5%+5) |
| Resistance (Ω) | 400Ω/4kΩ/40kΩ/400kΩ/4MΩ | | | ±(1.2%+5) |
| | 40MΩ | | | ±(1.5%+5) |
| Capacitance (F) | 51.2nF/512nF/5.12μF/51.2μF/100μF | | | ±(3%+5) |
| Display count | 3999 | | | |
| Power | Li-ion battery: 7.4V 3600mAh; DC adapter: 100V~240V, 50/60Hz input, 9V/4A output | | | |
| Display | 3.5 inch TFT LCD, 320x240 | | | |
| Product color | Red and grey | | | |
| Product net weight | 0.9kg | | | |
| Product size (W×H×D) | 199mm x 118 mm x 49mm | | | |
| Standard quantity per carton | 2pcs | | | |
| Standard carton size | 305mm x 190mm x 330mm | | | |
| Standard carton gross weight | 3.3kg | | 4.6kg | |

| Ordering Information | |
|----------------------|--|
| UTD1000DL | UTD1050DL: 50MHz, 12Kpts, 250MSa/s, 2-Channel |
| | UTD1025DL: 25MHz, 12Kpts, 250MSa/s, 2-Channel |
| UTD1000CL | UTD1050CL: 50MHz, 12Kpts, 200MSa/s, 1-Channel |
| | UTD1025CL: 25MHz, 12Kpts, 200MSa/s, 1-Channel |
| Standard Accessories | Power cord conforming to the standard of the destination country |
| | UT-H03: Passive probe x 2 (1 x, 10 x switchable, 60MHz)(1000DL) |
| | UT-H03: Passive probe x 1 (1 x, 10 x switchable, 60MHz)(1000CL) |
| | UT-M10: 1 Voltage/current converter: 40mA, 400mA (1000DL) |
| | UT-M04: 1 Voltage/current converter: 4A/6A (1000DL) |
| | UT-M07: current diverter: 10A (1000CL) |
| | UT-D17: USB Host to Mini USB data cable |
| | Power adapter : 1pc |
| | Multimeter Test Lead: 1 pair (one red, one black) |
| Portable bag | |